


**Important:** Read All Instructions Prior to Installation

**Function introduction**



**Product Data**

Output	LED Channel	4
	DC Voltage	24V DC
	Max. Current	Max. 4.16A/CH, CH1+CH2+CH3+CH4=4.16A
	Voltage Tolerance	± 1%
	Rated Power	max. 100W
Input	Voltage Range	100-240V AC
	Frequency Range	50/60Hz
	Power Factor (Typ.)	> 0.90 @ 230VAC
	Total Harmonic Distortion	THD ≤ 15% (@ full load / 230VAC)
	Efficiency (Typ.)	90% @ 230VAC full load
	AC Current (Typ.)	1.2A @ 100VAC, 0.5A @ 230VAC
	Inrush Current (Typ.)	COLD START Max. 50A at 230VAC
Control	Leakage Current	< 0.5mA /230VAC
	Dimming Interface	0/1-10V
	Dimming Range	0%-100%
Protection	Dimming Method	Pulse Width Modulation
	Over Current	Yes, recovers automatically after fault condition is removed
	Over Temperature	Yes, recovers automatically after fault condition is removed


Environment	Working Temp.	-20°C ~ +50°C
	Max. Case Temp.	75°C
	Working Humidity	10% ~ 95% RH non-condensing
	Storage Temp. & Humidity	-40°C ~ +80°C, 10% ~ 95% RH
Safety & EMC	Safety Standards	TUV EN61347-1, EN61347-2-13 approved
	Withstand Voltage	I/P-O/P: 3.75KVAC
	Isolation Resistance	I/P-O/P: 100M Ohms / 500VDC / 25°C / 70% RH
	EMC Emission	EN55015, EN61000-3-2, EN61000-3-3
	EMC Immunity	EN61547, EN61000-4-2,3,4,5,6,8,11, surge immunity Line-Line 1KV
Others	MTBF	193.6K hrs min. @ 230VAC full load and 25°C ambient temperature
	Dimension	244*64*32mm (L*W*H)

- Dimmable LED driver
- 100-240VAC wide input voltage
- Max. output power 100W total
- 4 channels 24VDC constant voltage output
- Class 1 power supply, full isolated plastic case
- High power factor and efficiency
- To control Single color LED lighting
- Built-in 0/1-10V interface
- Compatible with universal 0/1-10V signal
- IP20 rating
- Suitable for indoor LED lighting applications
- 5 years warranty


**Safety & Warnings**

- DO NOT install with power applied to device.
- DO NOT expose the device to moisture.

**Wiring Diagram**



## Product Dimension



## Installation



**Note:** when mounting the driver, please choose any one of the three fixing screw holes to fix with a screw at each end.